

To make transformer selection fast and easy, this selection guide compiles all Stancor transformers¹ & power supplies and arranges them by 1) Output Voltage, 2) Amperage (output at rated load), 3) Input Voltage, 4) AC/DC, and 5) Catalog Section Tab (Transformer Type).

Note that products may be listed more than once in the case of multi-tapped, center tapped or dual secondary outputs. The Table is constructed to show ALL output options for ALL transformers¹ and power supplies.

To use this table to identify part number selection(s): scroll down list to locate the required specification for each attribute.

1) Select Output Voltage Required.

2) Select Output Amps Required.

3) Select Input Voltage Required.

4) AC or DC?

5) Use Catalog Section Tab and (transformer type) to reference your final selection(s).

6) Identify Part Number(s) and use page and section to find additional specifications.

* = Center Tap Available

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
5.00	0.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-10	23	A
5.00	0.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-310	27	A
5.00	0.600	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-510	16	A
5.00	0.600	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-410	27	A
5.00	0.600	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-510	16	A
5.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-310	25	A
5.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-610	25	B
5.00	0.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-410	27	A
5.00	0.600	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4850	32	B

Example shown locating options for 5VDC @ 0.60A output with 120VAC input: STA-4850 Pg. 32 Sec. B

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
-12.00	0.300	120	DC	Domestic Power Sources (Desk-Top Regulated)		STAR-9007	34	C
1.25	5.000	117	AC	Power Transformer (Single Secondary)		P-6133	2	A
1.25	10.000	117/107	AC	Power Transformer (Single Secondary)		P-6454	2	A
2.50	0.500	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4125T	32	A
2.50	1.000	117	AC	Power Transformer (Single Secondary)		P-8629	2	A
2.50	3.000	117	AC	Power Transformer (Single Secondary)		P-6467	2	A
2.50	5.000	117	AC	Power Transformer (Single Secondary)	*	P-6133	2	A
2.50	10.000	117	AC	Power Transformer (Single Secondary)		P-6135	2	B
2.50	10.000	117/107	AC	Power Transformer (Single Secondary)	*	P-6454	2	A
3.00	0.350	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4130	32	A
3.00	0.500	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3530	32	A
3.15	0.300	117	AC	Power Transformer (Single Secondary)		P-8385	2	B
3.15	0.600	117	AC	Power Transformer (Single Secondary)		P-6465	2	B
3.15	0.600	230	AC	Power Transformer (Single Secondary)		P-8705	2	B
3.15	1.200	117	AC	Power Transformer (Single Secondary)		P-6134	2	C
3.15	3.000	117	AC	Power Transformer (Single Secondary)		P-6466	2	C
3.15	4.000	117	AC	Power Transformer (Single Secondary)		P-8648	2	D
3.15	6.000	117/107	AC	Power Transformer (Single Secondary)		P-6456	2	D
3.15	8.000	117	AC	Power Transformer (Single Secondary)		P-8651	2	D
3.15	10.000	117	AC	Power Transformer (Single Secondary)		P-6464	2	D
3.15	10.000	117/107	AC	Power Transformer (Single Secondary)		P-6308	2	E
3.15	20.000	117/107	AC	Power Transformer (Single Secondary)		P-6309	2	E
3.75	4.000	117	AC	Power Transformer (Single Secondary)		P-5015	2	E
3.75	8.000	117	AC	Power Transformer (Single Secondary)		P-6138	2	E
4.00	0.188	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-1	30	A
4.00	0.376	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-1	30	A
4.40	0.400	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3540	32	A
4.50	0.300	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3545B	32	B
5.00	0.110	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-210	27	A
5.00	0.110	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-210	27	A
5.00	0.120	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-610	25	B
5.00	0.200	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-210	25	A
5.00	0.220	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-210	27	A
5.00	0.220	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-210	27	A
5.00	0.250	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-310	27	A
5.00	0.250	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-310	27	A
5.00	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-310	25	A
5.00	0.400	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-210	25	A
5.00	0.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-310	16	A
5.00	0.500	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-310	27	A
5.00	0.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-10	23	A
5.00	0.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-310	27	A
5.00	0.600	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-510	16	A
5.00	0.600	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-410	27	A
5.00	0.600	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-510	16	A
5.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-310	25	A
5.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-610	25	B
5.00	0.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-410	27	A
5.00	0.600	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4850	32	B

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
5.00	1.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG05-10	23	A
5.00	1.000	117	AC	Power Transformer (Single Secondary)		P-8652	2	F
5.00	1.000	120	DC	Domestic Power Sources (Desk-Top Regulated)		STAR-9001	34	C
5.00	1.000	120	DC	Domestic Power Sources (Desk-Top Regulated)		STAR-9007	34	C
5.00	1.200	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-410	16	A
5.00	1.200	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-410	27	A
5.00	1.200	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-510	27	A
5.00	1.200	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-410	16	A
5.00	1.200	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-510	27	A
5.00	1.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-610	16	A
5.00	1.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-610	16	A
5.00	2.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG10-10	23	A
5.00	2.000	117	AC	Power Transformer (Single Secondary)		P-8653	2	F
5.00	2.400	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-510	27	A
5.00	2.400	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-510	27	A
5.00	2.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-710	16	A
5.00	2.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-710	16	A
5.00	3.000	117	AC	Power Transformer (Single Secondary)	*	P-6467	2	A
5.00	3.000	117	AC	Power Transformer (Single Secondary)		P-8380	2	F
5.00	4.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG20-10	23	A
5.00	4.000	117	AC	Power Transformer (Single Secondary)		P-5016	2	F
5.00	5.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-810	16	A
5.00	5.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC25-10	14	A
5.00	6.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG30-10	23	A
5.00	6.000	117	AC	Power Transformer (Single Secondary)		P-8655	2	G
5.00	8.000	117	AC	Power Transformer (Single Secondary)		P-8656	2	G
5.00	8.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC43-10	14	A
5.00	10.000	117	AC	Power Transformer (Single Secondary)	*	P-6135	2	B
5.00	11.200	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG56-10	23	A
5.00	16.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC80-10	14	A
5.00	26.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC130-10	14	A
5.00	35.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC175-10	14	A
6.00	0.100	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3560B	32	B
6.00	0.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3560	32	B
6.00	0.300	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3560A	32	C
6.00	0.500	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-0381F	36	A
6.00	0.600	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4160	32	C
6.00	0.800	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4160A	32	C
6.00	1.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6375	5	C
6.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4860	32	C
6.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4860-4	32	D
6.00	1.000	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-0797F	36	A
6.00	1.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4860A	32	D
6.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6375	5	C
6.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6376	5	C
6.00	2.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5760	32	D
6.00	3.300	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5760A	32	D
6.00	4.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6376	5	C
6.20	0.300	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-2100F	36	A

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
6.30	0.090	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-212	27	B
6.30	0.090	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-212	27	B
6.30	0.100	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-312	16	B
6.30	0.180	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-212	27	B
6.30	0.180	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-212	27	B
6.30	0.200	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-312	27	B
6.30	0.200	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-312	27	B
6.30	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-412	16	B
6.30	0.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-412	16	B
6.30	0.300	117	AC	Power Transformer (Single Secondary)	*	P-8385	2	B
6.30	0.350	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-18	30	B
6.30	0.400	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-312	27	B
6.30	0.400	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-12	23	B
6.30	0.400	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-312	27	B
6.30	0.450	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-612	25	C
6.30	0.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-512	16	B
6.30	0.500	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-412	27	B
6.30	0.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-512	16	B
6.30	0.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-412	27	B
6.30	0.600	117	AC	Power Transformer (Single Secondary)	*	P-6465	2	B
6.30	0.600	230	AC	Power Transformer (Single Secondary)	*	P-8705	2	B
6.30	0.700	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-18	30	B
6.30	0.800	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG05-12	23	B
6.30	0.900	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-612	25	C
6.30	0.900	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1212	25	C
6.30	1.000	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-412	27	B
6.30	1.000	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-512	27	B
6.30	1.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-412	27	B
6.30	1.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-512	27	B
6.30	1.000	117	AC	Power Transformer (Single Secondary)		P-8389	2	C
6.30	1.000	117	AC	Power Transformer (Single Secondary)		P-8384	2	I
6.30	1.200	117	AC	Power Transformer (Single Secondary)	*	P-6134	2	C
6.30	1.200	117	AC	Power Transformer (Single Secondary)		P-8190	2	C
6.30	1.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-612	16	B
6.30	1.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-612	16	B
6.30	1.500	117	AC	Power Transformer (Single Secondary)		P-8550	2	E
6.30	1.600	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-612	27	B
6.30	1.600	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG10-12	23	B
6.30	1.800	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1212	25	C
6.30	2.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-712	16	B
6.30	2.000	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-512	27	B
6.30	2.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-712	16	B
6.30	2.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-512	27	B
6.30	2.000	117	AC	Power Transformer (Single Secondary)		P-8130	3	D
6.30	2.000	230	AC	Power Transformer (Single Secondary)		P-8715	3	A
6.30	3.000	117	AC	Power Transformer (Single Secondary)	*	P-6466	2	C
6.30	3.000	117	AC	Power Transformer (Single Secondary)		P-8358	3	A
6.30	3.200	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-612	27	B
6.30	3.200	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG20-12	23	B

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
6.30	3.500	117	AC	Power Transformer (Single Primary, Multiple Secondaries)	*	P-6429	5	A
6.30	4.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-812	16	B
6.30	4.000	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC25-12	14	B
6.30	4.000	117	AC	Power Transformer (Single Secondary)	*	P-8648	2	D
6.30	4.000	117	AC	Power Transformer (Single Secondary)		P-8641	3	A
6.30	4.800	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG30-12	23	B
6.30	6.000	117/107	AC	Power Transformer (Single Secondary)	*	P-6456	2	D
6.30	6.800	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC43-12	14	B
6.30	8.000	117	AC	Power Transformer (Single Secondary)	*	P-8651	2	D
6.30	8.800	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG56-12	23	B
6.30	10.000	117	AC	Power Transformer (Single Secondary)	*	P-6464	2	D
6.30	10.000	117	AC	Power Transformer (Single Secondary)		P-8644	3	B
6.30	10.000	117/107	AC	Power Transformer (Single Secondary)	*	P-6308	2	E
6.30	12.600	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC80-12	14	B
6.30	20.000	117/107	AC	Power Transformer (Single Secondary)	*	P-6309	2	E
6.30	20.600	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC130-12	14	B
6.30	28.000	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC175-12	14	B
7.00	0.250	115	AC	Power Transformer (Single Secondary)		P-8553	3	B
7.00	1.000	115	AC	Power Transformer (Single Secondary)		P-8555	3	B
7.00	4.000	115	AC	Power Transformer (Single Secondary)		P-8557	3	B
7.00	6.000	115	AC	Power Transformer (Single Secondary)		P-8558	3	C
7.50	0.100	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-2	30	A
7.50	0.100	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-46	30	A
7.50	0.150	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-215	25	C
7.50	0.200	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-2	30	A
7.50	0.200	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-46	30	A
7.50	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-215	25	C
7.50	0.300	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3575A	32	E
7.50	0.450	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-315	25	C
7.50	0.500	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4175A	32	E
7.50	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4875	32	E
7.50	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4875-4	32	E
7.50	4.000	117	AC	Power Transformer (Single Secondary)	*	P-5015	2	E
7.50	8.000	117	AC	Power Transformer (Single Secondary)	*	P-6138	2	E
7.50	0.225	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-315	25	C
8.00	0.070	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-216	27	C
8.00	0.075	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-316	16	C
8.00	0.140	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-216	27	C
8.00	0.150	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-316	27	C
8.00	0.150	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-316	27	C
8.00	0.200	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-416	16	C
8.00	0.200	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-416	16	C
8.00	0.280	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-19	30	B
8.00	0.300	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-316	27	C
8.00	0.300	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-16	23	C
8.00	0.300	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-316	27	C
8.00	0.350	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-616	25	D
8.00	0.400	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-516	16	C
8.00	0.400	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-416	27	C

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
8.00	0.400	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-516	16	C
8.00	0.400	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-416	27	C
8.00	0.560	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-19	30	B
8.00	0.620	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG05-16	23	C
8.00	0.700	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-616	25	D
8.00	0.700	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1216	25	D
8.00	0.800	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-416	27	C
8.00	0.800	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-516	27	C
8.00	0.800	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-416	27	C
8.00	0.800	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-516	27	C
8.00	1.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-616	16	C
8.00	1.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-616	16	C
8.00	1.250	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-616	27	C
8.00	1.250	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG10-16	23	C
8.00	1.250	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-616	27	C
8.00	1.400	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1216	25	D
8.00	1.600	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-516	27	C
8.00	1.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-516	27	C
8.00	1.750	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-716	16	C
8.00	1.750	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-716	16	C
8.00	2.500	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-616	27	C
8.00	2.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG20-16	23	C
8.00	2.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-616	27	C
8.00	3.125	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-816	16	C
8.00	3.200	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC25-16	14	C
8.00	3.800	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG30-16	23	C
8.00	5.400	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC43-16	14	C
8.00	7.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG56-16	23	C
8.00	10.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC80-16	14	C
8.00	16.200	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC130-16	14	C
8.00	22.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC175-16	14	C
8.00	0.188	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-1	30	A
9.00	0.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4190C	32	F
9.00	0.200	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-2223F	36	A
9.00	0.300	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3590A	32	F
9.00	0.300	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4175A	32	E
9.00	0.300	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4190B	32	F
9.00	0.300	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-3309F	36	B
9.00	0.400	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4890B	32	G
9.00	0.500	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4190A	32	G
9.00	0.500	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4190D	32	G
9.00	0.500	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-1058F	36	B
9.00	0.700	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4190F	32	G
9.00	1.000	115	AC	Power Transformer (Single Secondary)		P-8691	3	C
9.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4890	32	H
9.00	1.000	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-0329F	36	B
9.00	1.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4890A	32	H
9.00	1.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4890A-4	32	H
9.00	1.500	115	AC	Power Transformer (Single Secondary)		P-8692	3	C

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
9.00	2.000	115	AC	Power Transformer (Single Secondary)		P-8693	3	C
9.00	3.400	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5790	32	H
9.00	0.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3590	32	F
10.00	0.055	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-220	27	D
10.00	0.060	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-320	16	D
10.00	0.110	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-210	27	A
10.00	0.110	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-210	27	A
10.00	0.110	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-220	27	D
10.00	0.120	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-320	27	D
10.00	0.120	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-320	27	D
10.00	0.150	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-320	16	D
10.00	0.150	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		SWC-320	16	D
10.00	0.200	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-210	25	A
10.00	0.200	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-420	25	D
10.00	0.240	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-320	27	D
10.00	0.240	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-20	23	D
10.00	0.240	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-320	27	D
10.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-310	16	A
10.00	0.250	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-310	27	A
10.00	0.250	115/230	AC	Power Transformer (Single Secondary)		P-8504	3	D
10.00	0.250	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG2H-10	23	A
10.00	0.250	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-520	25	D
10.00	0.250	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-310	27	A
10.00	0.300	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-520	16	D
10.00	0.300	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-420	27	D
10.00	0.300	115/230	AC	Power Transformer (Single Secondary)		P-8505	3	D
10.00	0.300	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-520	16	D
10.00	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-310	25	A
10.00	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-620	25	E
10.00	0.300	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-420	27	D
10.00	0.300	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4110A	33	A
10.00	0.400	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-420	25	D
10.00	0.500	115/230	AC	Power Transformer (Single Secondary)		P-8507	3	D
10.00	0.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG05-10	23	A
10.00	0.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG05-20	23	D
10.00	0.500	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-520	25	D
10.00	0.600	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-410	16	A
10.00	0.600	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-520	27	D
10.00	0.600	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-410	27	A
10.00	0.600	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-420	27	D
10.00	0.600	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-410	16	A
10.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-610	25	B
10.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-620	25	E
10.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1220	25	E
10.00	0.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-410	27	A
10.00	0.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-420	27	D
10.00	0.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-520	27	D
10.00	0.700	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4110	33	A
10.00	0.750	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-620	16	D

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
10.00	0.750	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-620	16	D
10.00	1.000	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-620	27	D
10.00	1.000	115/230	AC	Power Transformer (Single Secondary)		P-8508	3	D
10.00	1.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG10-10	23	A
10.00	1.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG10-20	23	D
10.00	1.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-620	27	D
10.00	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8652	2	F
10.00	1.000	117	AC	Power Transformer (Single Secondary)		P-8604	3	E
10.00	1.200	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-510	16	A
10.00	1.200	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-510	27	A
10.00	1.200	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-510	16	A
10.00	1.200	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1220	25	E
10.00	1.200	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-510	27	A
10.00	1.200	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-520	27	D
10.00	1.400	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-720	16	D
10.00	1.400	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-720	16	D
10.00	2.000	115	AC	Power Transformer (Single Secondary)		P-8559	3	E
10.00	2.000	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-620	27	D
10.00	2.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG20-10	23	A
10.00	2.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG20-20	23	D
10.00	2.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-620	27	D
10.00	2.000	117	AC	Power Transformer (Single Secondary)	*	P-8653	2	F
10.00	2.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-820	16	D
10.00	2.500	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC25-10	14	A
10.00	2.500	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC25-20	14	D
10.00	3.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-610	16	A
10.00	3.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-610	16	A
10.00	3.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG30-10	23	A
10.00	3.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG30-20	23	D
10.00	3.000	117	AC	Power Transformer (Single Secondary)	*	P-8380	2	F
10.00	4.000	115	AC	Power Transformer (Single Secondary)		P-8560	3	E
10.00	4.000	117	AC	Power Transformer (Single Secondary)	*	P-5016	2	F
10.00	4.300	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC43-10	14	A
10.00	4.400	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC43-20	14	D
10.00	5.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-710	16	A
10.00	5.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-710	16	A
10.00	5.600	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG56-10	23	A
10.00	5.600	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG56-20	23	D
10.00	6.000	117	AC	Power Transformer (Single Secondary)	*	P-8655	2	G
10.00	8.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC80-10	14	A
10.00	8.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC80-20	14	D
10.00	8.000	117	AC	Power Transformer (Single Secondary)	*	P-8656	2	G
10.00	10.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-810	16	A
10.00	13.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-10	14	A
10.00	13.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC130-20	14	D
10.00	17.500	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-10	14	A
10.00	17.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC175-20	14	D
12.00	0.045	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-224	28	A
12.00	0.050	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-324	16	E

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
12.00	0.050	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3512	33	A
12.00	0.090	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-224	28	A
12.00	0.090	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-224	28	A
12.00	0.100	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-324	28	A
12.00	0.100	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-324	28	A
12.00	0.100	117	AC	Power Transformer (Single Primary, Multiple Secondaries)	*	P-8361	5	A
12.00	0.100	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3512C	33	A
12.00	0.125	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-424	16	E
12.00	0.125	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-424	16	E
12.00	0.150	117	AC	Power Transformer (Single Secondary)		P-8390	2	G
12.00	0.150	117	AC	Power Transformer (Single Primary, Multiple Secondaries)	*	P-8362	5	B
12.00	0.167	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-424	25	E
12.00	0.180	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-20	30	C
12.00	0.200	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-324	28	A
12.00	0.200	115/230	AC	Power Transformer (Single Secondary)		P-8578	3	G
12.00	0.200	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-24	23	E
12.00	0.200	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-324	28	A
12.00	0.200	117	AC	Power Transformer (Single Secondary)		P-8395	3	F
12.00	0.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-300R	33	B
12.00	0.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3512B	33	B
12.00	0.200	230	AC	Power Transformer (Single Secondary)		P-8721	3	F
12.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-524	16	E
12.00	0.250	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-424	28	A
12.00	0.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-524	16	E
12.00	0.250	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-624	25	F
12.00	0.250	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-424	28	A
12.00	0.300	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4112B	33	B
12.00	0.300	120	DC	Domestic Power Sources (Desk-Top Regulated)		STAR-9007	34	C
12.00	0.300	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-3382F	36	B
12.00	0.333	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-424	25	E
12.00	0.350	117	AC	Power Transformer (Single Secondary)		P-8391	2	G
12.00	0.360	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-20	30	C
12.00	0.400	117	AC	Power Transformer (Single Secondary)		P-8396	3	G
12.00	0.400	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4112	33	B
12.00	0.400	230	AC	Power Transformer (Single Secondary)		P-8722	3	G
12.00	0.420	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG05-24	23	E
12.00	0.500	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-424	28	A
12.00	0.500	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-524	28	A
12.00	0.500	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-624	25	F
12.00	0.500	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1224	25	F
12.00	0.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-424	28	A
12.00	0.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-524	28	A
12.00	0.500	117	AC	Power Transformer (Single Primary, Multiple Secondaries)	*	P-8364	5	B
12.00	0.500	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4112A	33	C
12.00	0.500	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4112C	33	C
12.00	0.600	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4812D	33	C
12.00	0.625	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-624	16	E
12.00	0.625	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-624	16	E
12.00	0.700	117	AC	Power Transformer (Single Secondary)		P-8392	2	H

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
12.00	0.700	117	AC	Power Transformer (Single Secondary)		P-8397	3	G
12.00	0.700	230	AC	Power Transformer (Single Secondary)		P-8723	3	H
12.00	0.800	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-624	28	A
12.00	0.840	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG10-24	23	E
12.00	0.850	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4812B	33	C
12.00	1.000	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-524	28	A
12.00	1.000	115/230	AC	Power Transformer (Single Secondary)		P-8575	3	H
12.00	1.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6375	5	C
12.00	1.000	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1224	25	F
12.00	1.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-524	28	A
12.00	1.000	117	AC	Power Transformer (Single Secondary)		P-8661	3	H
12.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4812A-4	33	D
12.00	1.000	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-1454FD	36	C
12.00	1.200	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-724	16	E
12.00	1.200	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-724	16	E
12.00	1.200	117	AC	Power Transformer (Single Secondary)		P-8393	2	H
12.00	1.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5712	33	D
12.00	1.200	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5712-4	33	D
12.00	1.200	120	DC	Domestic Power Sources (Desk-Top Regulated)		STAR-9004	34	C
12.00	1.200	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-1948FD	36	C
12.00	1.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-624	28	A
12.00	1.660	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG20-24	23	E
12.00	2.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-824	16	E
12.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6376	5	C
12.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6377	5	C
12.00	2.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC25-24	14	E
12.00	2.000	117	AC	Power Transformer (Single Secondary)		P-8657	2	H
12.00	2.000	117	AC	Power Transformer (Single Secondary)		P-8662	3	H
12.00	2.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-6612	33	E
12.00	2.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG30-24	23	E
12.00	3.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-6612B	33	E
12.00	3.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC43-24	14	E
12.00	4.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6377	5	C
12.00	4.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6378	5	C
12.00	4.000	117	AC	Power Transformer (Single Secondary)		P-8658	2	H
12.00	4.000	117	AC	Power Transformer (Single Secondary)		P-8663	3	I
12.00	4.660	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG56-24	23	E
12.00	6.000	117	AC	Power Transformer (Single Secondary)		P-8659	2	I
12.00	6.000	117	AC	Power Transformer (Single Secondary)		P-8664	3	I
12.00	6.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC80-24	14	E
12.00	8.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6378	5	C
12.00	8.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6379	5	C
12.00	8.000	117	AC	Power Transformer (Single Secondary)		P-8660	2	I
12.00	8.000	117	AC	Power Transformer (Single Secondary)		P-8665	3	I
12.00	10.000	115	AC	Power Transformer (Single Secondary)		P-8695	3	I
12.00	10.800	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC130-24	14	E
12.00	12.000	117	AC	Power Transformer (Single Secondary)		P-8666	4	A
12.00	14.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC175-24	14	E
12.00	16.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6379	5	C

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
12.00	0.045	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-224	28	A
12.00	0.085	117	AC	Power Transformer (Single Secondary)		P-8394	3	F
12.25	0.250	117	AC	Power Transformer (Single Secondary)		P-8607	4	A
12.60	0.090	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-212	27	B
12.60	0.090	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-212	27	B
12.60	0.200	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-312	16	B
12.60	0.200	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-312	27	B
12.60	0.200	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG2H-12	23	B
12.60	0.200	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-312	27	B
12.60	0.350	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-18	30	B
12.60	0.400	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG05-12	23	B
12.60	0.450	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-612	25	C
12.60	0.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-412	16	B
12.60	0.500	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-412	27	B
12.60	0.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-412	16	B
12.60	0.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-412	27	B
12.60	0.800	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG10-12	23	B
12.60	0.900	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-1212	25	C
12.60	1.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-512	16	B
12.60	1.000	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-512	27	B
12.60	1.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-512	16	B
12.60	1.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-512	27	B
12.60	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8384	2	I
12.60	1.000	117	AC	Power Transformer (Single Secondary)		P-8180	4	A
12.60	1.400	117	AC	Power Transformer (Single Secondary)		P-8388	4	B
12.60	1.500	117	AC	Power Transformer (Single Secondary)	*	P-8550	2	I
12.60	1.600	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-612	27	B
12.60	1.600	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG20-12	23	B
12.60	2.000	115/230	AC	Power Transformer (Single Secondary)		P-8574	4	B
12.60	2.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC25-12	14	B
12.60	2.000	117	AC	Power Transformer (Single Secondary)	*	P-8130	3	A
12.60	2.000	117	AC	Power Transformer (Single Secondary)		P-8357	4	B
12.60	2.000	230	AC	Power Transformer (Single Secondary)	*	P-8715	3	A
12.60	2.400	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG30-12	23	B
12.60	2.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-612	16	B
12.60	2.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-612	16	B
12.60	3.000	117	AC	Power Transformer (Single Secondary)	*	P-8358	3	A
12.60	3.400	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC43-12	14	B
12.60	4.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-712	16	B
12.60	4.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-712	16	B
12.60	4.000	117	AC	Power Transformer (Single Secondary)	*	P-8641	3	A
12.60	4.400	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG56-12	23	B
12.60	6.300	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC80-12	14	B
12.60	8.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-812	16	B
12.60	10.000	117	AC	Power Transformer (Single Secondary)	*	P-8644	3	B
12.60	10.300	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-12	14	B
12.60	14.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-12	14	B
13.00	0.250	117	AC	Power Transformer (Single Secondary)		P-8607	4	A
13.40	1.000	117	AC	Power Transformer (Single Secondary)		P-8609	4	C

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
13.50	1.300	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5713	33	E
13.50	1.700	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5713A	33	E
13.50	1.700	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5713AC	33	F
13.75	0.250	117	AC	Power Transformer (Single Secondary)		P-8607	4	A
14.00	0.040	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-228	28	B
14.00	0.040	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-228	28	B
14.00	0.043	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-328	17	F
14.00	0.080	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-228	28	B
14.00	0.080	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-228	28	B
14.00	0.085	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-328	28	B
14.00	0.100	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-428	17	F
14.00	0.100	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-428	17	F
14.00	0.170	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-328	28	B
14.00	0.170	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-328	28	B
14.00	0.175	117	AC	Power Transformer (Single Secondary)		P-8601	4	C
14.00	0.180	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-28	23	F
14.00	0.200	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-428	28	B
14.00	0.210	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-528	17	F
14.00	0.210	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-528	17	F
14.00	0.250	115	AC	Power Transformer (Single Secondary)	*	P-8553	3	B
14.00	0.300	117	AC	Power Transformer (Single Secondary)		P-8602	4	C
14.00	0.360	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG05-28	23	F
14.00	0.400	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-428	28	B
14.00	0.420	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-528	28	B
14.00	0.420	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-528	28	B
14.00	0.550	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-628	17	F
14.00	0.550	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-628	17	F
14.00	0.700	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-628	28	B
14.00	0.700	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-628	28	B
14.00	0.720	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG10-28	23	F
14.00	0.840	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-528	28	B
14.00	0.840	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-528	28	B
14.00	0.850	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-328	28	B
14.00	1.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-728	17	F
14.00	1.000	115	AC	Power Transformer (Single Secondary)	*	P-8555	3	B
14.00	1.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-728	17	F
14.00	1.000	117	AC	Power Transformer (Single Secondary)		P-8667	4	C
14.00	1.300	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-828	17	F
14.00	1.400	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-628	28	B
14.00	1.400	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-628	28	B
14.00	1.440	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG20-28	23	F
14.00	1.800	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC25-28	14	F
14.00	2.000	117	AC	Power Transformer (Single Secondary)		P-8668	4	D
14.00	2.120	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG30-28	23	F
14.00	3.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC43-28	14	F
14.00	4.000	115	AC	Power Transformer (Single Secondary)	*	P-8557	3	B
14.00	4.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG56-28	23	F
14.00	4.000	117	AC	Power Transformer (Single Secondary)		P-8669	4	D
14.00	5.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC80-28	14	F

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
14.00	6.000	115	AC	Power Transformer (Single Secondary)	*	P-8558	3	C
14.00	6.000	117	AC	Power Transformer (Single Secondary)		P-8670	4	D
14.00	9.200	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC130-28	14	F
14.00	12.500	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC175-28	14	F
14.50	0.250	117	AC	Power Transformer (Single Secondary)		P-8607	4	A
14.50	0.800	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4814	33	F
14.50	0.800	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-0354F	36	C
15.00	0.050	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-3	30	A
15.00	0.050	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-8	30	A
15.00	0.100	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-2	30	A
15.00	0.100	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-3	30	A
15.00	0.100	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-8	30	A
15.00	0.100	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-46	30	A
15.00	0.150	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-215	25	C
15.00	0.250	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-23	30	D
15.00	0.500	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-23	30	D
15.00	0.600	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4815	33	F
15.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5715	33	F
15.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5715-4	33	G
15.00	1.000	230/50HZ	DC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-1972F	36	D
15.00	2.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-6615	33	G
15.00	0.225	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-315	25	C
16.00	0.070	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-216	27	C
16.00	0.150	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-316	16	C
16.00	0.150	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-316	27	C
16.00	0.150	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG2H-16	23	C
16.00	0.150	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-316	27	C
16.00	0.250	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4116	33	G
16.00	0.280	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-19	30	B
16.00	0.310	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG05-16	23	C
16.00	0.350	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-616	25	D
16.00	0.400	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-416	16	C
16.00	0.400	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-416	27	C
16.00	0.400	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-416	16	C
16.00	0.400	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-416	27	C
16.00	0.620	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG10-16	23	C
16.00	0.700	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-1216	25	D
16.00	0.800	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-516	16	C
16.00	0.800	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-516	27	C
16.00	0.800	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-516	16	C
16.00	0.800	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-516	27	C
16.00	1.250	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-616	27	C
16.00	1.250	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG20-16	23	C
16.00	1.250	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-616	27	C
16.00	1.600	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)	*	TGC25-16	14	C
16.00	1.900	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG30-16	23	C
16.00	2.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-616	16	C
16.00	2.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-616	16	C
16.00	2.700	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)	*	TGC43-16	14	C

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
16.00	3.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-716	16	C
16.00	3.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-716	16	C
16.00	3.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG56-16	23	C
16.00	5.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC80-16	14	C
16.00	6.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-816	16	C
16.00	8.100	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-16	14	C
16.00	11.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-16	14	C
16.00	0.188	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-432	28	C
16.00	0.188	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-432	28	C
16.00	0.376	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-432	28	C
16.00	0.376	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-432	28	C
17.00	0.170	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-634	25	F
17.00	0.340	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-634	25	F
17.00	0.340	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1234	25	F
17.00	0.680	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1234	25	F
18.00	0.030	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-236	28	D
18.00	0.030	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-236	28	D
18.00	0.033	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-336	17	G
18.00	0.060	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-236	28	D
18.00	0.060	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-236	28	D
18.00	0.065	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-336	28	D
18.00	0.085	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-436	17	G
18.00	0.085	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-436	17	G
18.00	0.130	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-336	28	D
18.00	0.140	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG2H-36	24	A
18.00	0.170	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-436	28	D
18.00	0.170	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-436	28	D
18.00	0.175	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-536	17	G
18.00	0.175	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-536	17	G
18.00	0.280	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG05-36	24	A
18.00	0.300	117	AC	Power Transformer (Single Secondary)		P-8612	4	E
18.00	0.300	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4118	33	G
18.00	0.340	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-436	28	D
18.00	0.340	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-436	28	D
18.00	0.350	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-536	28	D
18.00	0.350	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-536	28	D
18.00	0.425	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-636	17	G
18.00	0.425	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-636	17	G
18.00	0.550	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-636	28	D
18.00	0.550	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-636	28	D
18.00	0.550	117	AC	Power Transformer (Single Secondary)		P-8613	4	E
18.00	0.560	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG10-36	24	A
18.00	0.700	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-536	28	D
18.00	0.700	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-536	28	D
18.00	0.750	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-736	17	G
18.00	0.750	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-736	17	G
18.00	1.000	115	AC	Power Transformer (Single Secondary)	*	P-8691	3	C
18.00	1.000	115	AC	Power Transformer (Single Secondary)	*	P-8684	4	G
18.00	1.000	117	AC	Power Transformer (Single Secondary)		P-8671	4	E

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
18.00	1.100	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-636	28	D
18.00	1.100	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-636	28	D
18.00	1.120	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG20-36	24	A
18.00	1.400	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-836	17	G
18.00	1.400	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC25-36	14	G
18.00	1.500	115	AC	Power Transformer (Single Secondary)	*	P-8692	3	C
18.00	1.640	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG30-36	24	A
18.00	2.000	115	AC	Power Transformer (Single Secondary)	*	P-8693	3	C
18.00	2.000	117	AC	Power Transformer (Single Secondary)		P-8672	4	E
18.00	2.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-6618	33	H
18.00	2.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-6618-4	33	H
18.00	2.400	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC43-36	14	G
18.00	3.120	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)		TG56-36	24	A
18.00	4.000	117	AC	Power Transformer (Single Secondary)		P-8673	4	F
18.00	4.400	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC80-36	14	G
18.00	6.000	117	AC	Power Transformer (Single Secondary)		P-8674	4	F
18.00	7.200	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC130-36	14	G
18.00	9.600	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)		TGC175-36	14	G
18.00	0.135	117	AC	Power Transformer (Single Secondary)		P-8611	4	D
18.50	0.080	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3518	33	H
20.00	0.055	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-220	27	D
20.00	0.120	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-320	16	D
20.00	0.120	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-320	27	D
20.00	0.120	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG2H-20	23	D
20.00	0.120	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-320	27	D
20.00	0.150	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-640	25	G
20.00	0.200	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-420	25	D
20.00	0.250	115/230	AC	Power Transformer (Single Secondary)	*	P-8504	3	D
20.00	0.250	115/230	AC	Power Transformer (Single Secondary)		P-8542	4	F
20.00	0.250	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG05-20	23	D
20.00	0.250	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-520	25	D
20.00	0.280	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4120	33	H
20.00	0.300	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-420	16	D
20.00	0.300	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-420	27	D
20.00	0.300	115/230	AC	Power Transformer (Single Secondary)	*	P-8505	3	D
20.00	0.300	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-420	16	D
20.00	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-620	25	E
20.00	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-640	25	G
20.00	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1240	25	G
20.00	0.300	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-420	27	D
20.00	0.500	115/230	AC	Power Transformer (Single Secondary)	*	P-8507	3	D
20.00	0.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG10-20	23	D
20.00	0.600	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-520	16	D
20.00	0.600	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-520	16	D
20.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-1220	25	E
20.00	0.600	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-1240	25	G
20.00	0.600	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-520	27	D
20.00	0.700	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4820	33	H

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
20.00	1.000	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-620	27	D
20.00	1.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG20-20	23	D
20.00	1.000	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-620	27	D
20.00	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8604	3	E
20.00	1.250	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC25-20	14	D
20.00	1.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-620	16	D
20.00	1.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-620	16	D
20.00	1.500	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG30-20	23	D
20.00	2.000	115	AC	Power Transformer (Single Secondary)	*	P-8559	3	E
20.00	2.200	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC43-20	14	D
20.00	2.800	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-720	16	D
20.00	2.800	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-720	16	D
20.00	2.800	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG56-20	23	D
20.00	4.000	115	AC	Power Transformer (Single Secondary)	*	P-8560	3	E
20.00	4.000	115	AC	Power Transformer (Single Secondary)		P-8566	4	F
20.00	4.000	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC80-20	14	D
20.00	5.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-820	16	D
20.00	6.500	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-20	14	D
20.00	8.800	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-20	14	D
20.00	0.112	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-17	30	C
20.00	0.224	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-17	30	C
24.00	0.023	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-248	28	E
24.00	0.025	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-348	17	H
24.00	0.045	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-224	28	A
24.00	0.046	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-248	28	E
24.00	0.050	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-348	28	E
24.00	0.050	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-3524	34	A
24.00	0.060	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-448	17	H
24.00	0.060	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-448	17	H
24.00	0.100	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-324	16	E
24.00	0.100	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-324	28	A
24.00	0.100	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG2H-24	23	E
24.00	0.100	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-324	28	A
24.00	0.100	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-348	28	E
24.00	0.125	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-548	17	H
24.00	0.125	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-548	17	H
24.00	0.167	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-424	25	E
24.00	0.180	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-20	30	C
24.00	0.200	115/230	AC	Power Transformer (Single Secondary)	*	P-8578	3	G
24.00	0.200	117	AC	Power Transformer (Single Secondary)	*	P-8395	3	F
24.00	0.200	230	AC	Power Transformer (Single Secondary)	*	P-8721	3	F
24.00	0.210	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG05-24	23	E
24.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-424	16	E
24.00	0.250	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-424	28	A
24.00	0.250	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8615	5	D
24.00	0.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-424	16	E
24.00	0.250	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-624	25	F
24.00	0.250	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-424	28	A
24.00	0.250	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-448	28	E

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
24.00	0.300	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4124	34	A
24.00	0.315	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-648	17	H
24.00	0.315	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-648	17	H
24.00	0.400	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-648	28	E
24.00	0.400	117	AC	Power Transformer (Single Secondary)	*	P-8396	3	G
24.00	0.400	230	AC	Power Transformer (Single Secondary)	*	P-8722	3	G
24.00	0.400	230/50HZ	AC	European Power Sources (Desk-Top and Wall Plug-In)		STAF-2098F	36	D
24.00	0.420	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG10-24	23	E
24.00	0.450	120	AC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4824B	34	A
24.00	0.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-524	16	E
24.00	0.500	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-524	28	A
24.00	0.500	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8615	5	D
24.00	0.500	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8616	5	D
24.00	0.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-524	16	E
24.00	0.500	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-1224	25	F
24.00	0.500	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-524	28	A
24.00	0.600	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-748	17	H
24.00	0.600	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-748	17	H
24.00	0.600	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-4824AT	34	B
24.00	0.700	117	AC	Power Transformer (Single Secondary)	*	P-8397	3	G
24.00	0.700	230	AC	Power Transformer (Single Secondary)	*	P-8723	3	H
24.00	0.800	115	AC	Printed Circuit Transformers ("Side-Winder")		SW-648	28	E
24.00	0.800	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-624	28	A
24.00	0.830	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG20-24	23	E
24.00	1.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-848	17	H
24.00	1.000	115	AC	Power Transformer (Single Secondary)		P-8551	3	E
24.00	1.000	115/230	AC	Power Transformer (Single Secondary)	*	P-8575	3	H
24.00	1.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8616	5	D
24.00	1.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8617	5	D
24.00	1.000	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)	*	TGC25-24	14	E
24.00	1.000	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-58	30	D
24.00	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8661	3	H
24.00	1.000	117	AC	Power Transformer (Single Secondary)		P-8605	4	F
24.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5724AT	34	B
24.00	1.000	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-5724AT-4	34	B
24.00	1.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-624	16	E
24.00	1.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-624	16	E
24.00	1.250	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG30-24	23	E
24.00	1.500	120	DC	Domestic Power Sources (Desk-Top and Wall Plug-In)		STA-6624	34	B
24.00	1.670	120	AC	Class 2 Transformers		T40-24F1	43	B
24.00	1.670	120	AC	Class 2 Transformers		T40-24M1	43	C
24.00	1.670	120	AC	Class 2 Transformers		T40-24S1	43	D
24.00	1.670	120	AC	Class 2 Transformers		592-9012	43	A
24.00	1.670	120/208/240	AC	Class 2 Transformers		592-9018	43	A
24.00	1.670	120/208/240	AC	Class 2 Transformers		T40-24	43	B
24.00	1.670	120/208/240	AC	Class 2 Transformers		T40-24F3	43	B
24.00	1.670	120/208/240	AC	Class 2 Transformers		T40-24S3	43	D
24.00	1.670	120/240	AC	Class 2 Transformers		592-9016	43	A
24.00	1.670	208/240	AC	Class 2 Transformers		592-9017	43	A

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
24.00	1.670	208/240	AC	Class 2 Transformers		T40-24F2	43	B
24.00	1.670	208/240	AC	Class 2 Transformers		T40-24M2	43	C
24.00	1.670	208/240	AC	Class 2 Transformers		T40-24S2	43	D
24.00	1.670	240	AC	Class 2 Transformers		592-9013	43	A
24.00	1.800	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC43-24	14	E
24.00	2.000	115	AC	Power Transformer (Single Secondary)		P-8694	3	F
24.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6377	5	C
24.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8617	5	D
24.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8618	5	D
24.00	2.000	117	AC	Power Transformer (Single Secondary)	*	P-8662	3	H
24.00	2.080	120/208/240	AC	Class 2 Transformers		T50-24F3	43	B
24.00	2.080	120/208/240	AC	Class 2 Transformers		T40-24M3	43	C
24.00	2.080	120/208/240	AC	Class 2 Transformers		T50-24M3	43	C
24.00	2.080	120/208/240	AC	Class 2 Transformers		T50-24S3	43	D
24.00	2.080	120/208/240	AC	Class 2 Transformers		T50-24C3	43	E
24.00	2.330	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG56-24	23	E
24.00	2.400	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-724	16	E
24.00	2.400	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-724	16	E
24.00	2.500	120/208/240	AC	Class 2 Transformers		T60-24C3	43	E
24.00	3.120	120/208/240	AC	Class 2 Transformers		T75-24C3	43	E
24.00	3.300	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC80-24	14	E
24.00	4.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-824	16	E
24.00	4.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6378	5	C
24.00	4.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8618	5	D
24.00	4.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8619	5	D
24.00	4.000	117	AC	Power Transformer (Single Secondary)	*	P-8663	3	I
24.00	5.400	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-24	14	E
24.00	6.000	117	AC	Power Transformer (Single Secondary)	*	P-8664	3	I
24.00	7.300	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-24	14	E
24.00	8.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-6379	5	C
24.00	8.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8619	5	D
24.00	8.000	117	AC	Power Transformer (Single Secondary)	*	P-8665	3	I
24.00	10.000	115	AC	Power Transformer (Single Secondary)	*	P-8695	3	I
24.00	12.000	117	AC	Power Transformer (Single Secondary)	*	P-8666	4	A
24.00	0.023	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-248	28	E
24.00	0.045	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-224	28	A
24.00	0.046	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-248	28	E
24.00	0.085	117	AC	Power Transformer (Single Secondary)	*	P-8394	3	F
24.00	0.125	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")		DSW-448	28	E
24.50	0.250	117	AC	Power Transformer (Single Secondary)	*	P-8607	4	A
25.00	4.000	120	AC	Class 2 Transformers		T100-25C1	43	E
25.00	4.000	208/240	AC	Class 2 Transformers		T100-25C2	43	E
25.20	1.000	117	AC	Power Transformer (Single Secondary)		P-6469	4	A
25.20	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8180	4	A
25.20	1.000	230	AC	Power Transformer (Single Secondary)		P-8707	4	A
25.20	2.000	115/230	AC	Power Transformer (Single Secondary)	*	P-8574	4	B
25.20	2.000	117	AC	Power Transformer (Single Secondary)	*	P-8357	4	B
25.20	2.800	117	AC	Power Transformer (Single Secondary)	*	P-8388	4	B
26.00	0.250	117	AC	Power Transformer (Single Secondary)	*	P-8607	4	A

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
26.80	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8609	4	C
27.00	0.084	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-14	30	C
27.00	0.168	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)		PPC-14	30	C
27.50	0.250	117	AC	Power Transformer (Single Secondary)	*	P-8607	4	A
28.00	0.010	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-356	17	I
28.00	0.025	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-456	17	I
28.00	0.040	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-228	28	B
28.00	0.040	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-228	28	B
28.00	0.050	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-556	17	I
28.00	0.055	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-456	17	I
28.00	0.085	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-328	17	F
28.00	0.085	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-328	28	B
28.00	0.090	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG2H-28	23	F
28.00	0.090	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-256	25	G
28.00	0.100	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-656	25	H
28.00	0.110	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-556	17	I
28.00	0.125	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-656	17	I
28.00	0.175	117	AC	Power Transformer (Single Secondary)	*	P-8601	4	C
28.00	0.180	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG05-28	23	F
28.00	0.200	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-428	17	F
28.00	0.200	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-428	28	B
28.00	0.200	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-428	17	F
28.00	0.200	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-656	25	H
28.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-756	17	I
28.00	0.270	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-656	17	I
28.00	0.300	117	AC	Power Transformer (Single Secondary)	*	P-8602	4	C
28.00	0.360	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG10-28	23	F
28.00	0.420	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-528	17	F
28.00	0.420	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-528	28	B
28.00	0.420	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-528	17	F
28.00	0.420	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-528	28	B
28.00	0.425	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-856	17	I
28.00	0.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-756	17	I
28.00	0.700	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-628	28	B
28.00	0.700	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-628	28	B
28.00	0.720	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG20-28	23	F
28.00	0.900	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)	*	TGC25-28	14	F
28.00	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8667	4	C
28.00	1.060	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG30-28	23	F
28.00	1.100	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-628	17	F
28.00	1.100	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-628	17	F
28.00	1.500	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)	*	TGC43-28	14	F
28.00	2.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-728	17	F
28.00	2.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-728	17	F
28.00	2.000	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG56-28	23	F
28.00	2.000	117	AC	Power Transformer (Single Secondary)	*	P-8668	4	D
28.00	2.800	115/230	AC	Chassis Mount Power Transformers (TransGlobal Transformers)	*	TGC80-28	14	F
28.00	3.600	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-828	17	F
28.00	4.000	117	AC	Power Transformer (Single Secondary)	*	P-8669	4	D

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
28.00	4.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-28	14	F
28.00	6.000	117	AC	Power Transformer (Single Secondary)	*	P-8670	4	D
28.00	6.250	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-28	14	F
28.00	0.045	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-256	25	G
28.00	0.085	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-328	28	B
29.00	0.250	117	AC	Power Transformer (Single Secondary)	*	P-8607	4	A
30.00	0.050	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-3	30	A
30.00	0.050	115/230	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-8	30	A
30.00	0.250	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-23	30	D
32.00	0.188	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-432	28	C
32.00	0.188	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-432	28	C
34.00	0.170	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-634	25	F
34.00	0.340	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-1234	25	F
36.00	0.030	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-236	28	D
36.00	0.030	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-236	28	D
36.00	0.065	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-336	17	G
36.00	0.070	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG2H-36	24	A
36.00	0.140	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG05-36	24	A
36.00	0.170	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-436	17	G
36.00	0.170	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-436	28	D
36.00	0.170	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-436	17	G
36.00	0.170	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-436	28	D
36.00	0.280	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG10-36	24	A
36.00	0.300	117	AC	Power Transformer (Single Secondary)	*	P-8612	4	E
36.00	0.350	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-536	17	G
36.00	0.350	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-536	28	D
36.00	0.350	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-536	17	G
36.00	0.350	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-536	28	D
36.00	0.550	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-636	28	D
36.00	0.550	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-636	28	D
36.00	0.550	117	AC	Power Transformer (Single Secondary)	*	P-8613	4	E
36.00	0.560	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG20-36	24	A
36.00	0.700	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC25-36	14	G
36.00	0.820	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG30-36	24	A
36.00	0.850	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-636	17	G
36.00	0.850	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-636	17	G
36.00	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8671	4	E
36.00	1.200	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC43-36	14	G
36.00	1.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-736	17	G
36.00	1.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-736	17	G
36.00	1.560	115/230	AC	Printed Circuit Transformers (TransGlobal Printed Circuit Mount)	*	TG56-36	24	A
36.00	2.000	117	AC	Power Transformer (Single Secondary)	*	P-8672	4	E
36.00	2.200	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC80-36	14	G
36.00	2.800	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-836	17	G
36.00	3.600	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-36	14	G
36.00	4.000	117	AC	Power Transformer (Single Secondary)	*	P-8673	4	F
36.00	4.800	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-36	14	G
36.00	6.000	117	AC	Power Transformer (Single Secondary)	*	P-8674	4	F
36.00	0.065	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-336	28	D

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
36.00	0.135	117	AC	Power Transformer (Single Secondary)	*	P-8611	4	D
40.00	0.150	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-640	25	G
40.00	0.250	115/230	AC	Power Transformer (Single Secondary)	*	P-8542	4	F
40.00	0.300	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-1240	25	G
40.00	4.000	115	AC	Power Transformer (Single Secondary)	*	P-8566	4	F
40.00	0.112	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-17	30	C
48.00	0.023	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-248	28	E
48.00	0.050	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-348	17	H
48.00	0.050	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-348	28	E
48.00	0.120	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-448	17	H
48.00	0.120	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-448	17	H
48.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-548	17	H
48.00	0.250	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8615	5	D
48.00	0.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-548	17	H
48.00	0.400	115	AC	Printed Circuit Transformers ("Side-Winder")	*	SW-648	28	E
48.00	0.500	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8616	5	D
48.00	0.630	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-648	17	H
48.00	0.630	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-648	17	H
48.00	1.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8617	5	D
48.00	1.000	117	AC	Power Transformer (Single Secondary)	*	P-8605	4	F
48.00	1.200	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-748	17	H
48.00	1.200	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-748	17	H
48.00	2.000	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-848	17	H
48.00	2.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8618	5	D
48.00	4.000	115/230	AC	Power Transformer (Dual Primary, Dual Secondary)		P-8619	5	D
48.00	0.023	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-248	28	E
48.00	0.125	115/230	AC	Printed Circuit Transformer (Dual "Side-Winder")	*	DSW-448	28	E
54.00	0.084	115	AC	Printed Circuit Transformers (Plug-In Printed Circuit Series)	*	PPC-14	30	C
56.00	0.020	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-356	17	I
56.00	0.050	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-456	17	I
56.00	0.100	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-556	17	I
56.00	0.100	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-656	25	H
56.00	0.110	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-456	17	I
56.00	0.220	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-556	17	I
56.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-656	17	I
56.00	0.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-756	17	I
56.00	0.540	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-656	17	I
56.00	0.850	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-856	17	I
56.00	1.000	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-756	17	I
56.00	0.045	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-256	25	G
60.00	0.010	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-3120	17	J
60.00	0.025	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-4120	17	J
60.00	0.025	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-4120	17	J
60.00	0.050	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-5120	17	J
60.00	0.050	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-5120	17	J
60.00	0.125	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-6120	17	J
60.00	0.125	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-6120	17	J
60.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-7120	17	J
60.00	0.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")		DSWC-7120	17	J
60.00	0.425	115	AC	Chassis Mount Power Transformers ("Side-Winder")		SWC-8120	17	J
115.00	0.005	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-6413	38	E
115.00	0.050	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-6230	25	I
115.00	0.050	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-12230	25	I
115.00	0.100	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-12230	25	I
115.00	0.130	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-6411	38	E
115.00	0.220	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC25-230	14	H
115.00	0.300	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-6412	38	E

QUICK SELECTION GUIDE

Transformer and Power Supplies

Output Voltage	Output Amps	Input Voltage (AC)	Output AC/DC	Catalog Section (transformer type)	C.T.	STANCOR Part No.	Pg.	Sec.
115.00	0.350	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-6287	38	A
115.00	0.380	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC43-230	14	H
115.00	0.430	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-6410	38	E
115.00	0.430	115/230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-6406	38	F
115.00	0.430	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8620	38	A
115.00	0.650	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8622	38	F
115.00	0.650	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-75	38	A
115.00	0.700	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC80-230	14	H
115.00	0.740	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8630	38	A
115.00	0.870	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GIS-100	38	G
115.00	0.870	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-100	38	A
115.00	0.870	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GISD-100	38	H
115.00	1.100	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8631	38	B
115.00	1.140	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC130-230	14	H
115.00	1.300	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GIS-150	38	G
115.00	1.300	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)	*	P-8622	38	F
115.00	1.300	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-150	38	B
115.00	1.300	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GISD-150	38	H
115.00	1.520	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)		TGC175-230	14	H
115.00	1.740	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8632	38	B
115.00	2.170	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GIS-250	38	G
115.00	2.170	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GISD-250	38	H
115.00	2.200	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-250	38	B
115.00	2.600	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-300	38	B
115.00	3.000	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-350	38	C
115.00	3.500	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8634	38	C
115.00	4.300	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-500	38	C
115.00	4.350	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GIS-500	38	G
115.00	4.350	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GISD-500	38	H
115.00	6.500	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-750	38	C
115.00	8.700	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GIS-1000	38	G
115.00	8.700	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-1000	38	C
115.00	8.700	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GISD-1000	38	H
115.00	13.000	230	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		GSD-1500	38	C
115.00	0.025	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)		LB-6230	25	I
120.00	0.020	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-3120	17	J
120.00	0.050	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-4120	17	J
120.00	0.050	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-4120	17	J
120.00	0.100	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-5120	17	J
120.00	0.100	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-5120	17	J
120.00	0.250	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-6120	17	J
120.00	0.250	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-6120	17	J
120.00	0.500	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-7120	17	J
120.00	0.500	115/230	AC	Chassis Mount Power Transformers (Dual "Side-Winder")	*	DSWC-7120	17	J
120.00	0.850	115	AC	Chassis Mount Power Transformers ("Side-Winder")	*	SWC-8120	17	J
230.00	0.050	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-12230	25	I
230.00	0.110	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC25-230	14	H
230.00	0.190	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC43-230	14	H
230.00	0.350	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC80-230	14	H
230.00	0.540	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8638	38	D
230.00	0.570	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC130-230	14	H
230.00	0.650	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8622	38	F
230.00	0.760	115/230	AC	Chassis Mount Power Transformers (Transglobal Transformers)	*	TGC175-230	14	H
230.00	1.300	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8639	38	D
230.00	2.170	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8640	38	D
230.00	4.350	115	AC	Auto/Isolation Transformers (Step-Up, Step-Down and Isolation)		P-8689	38	D
230.00	0.025	115/230	AC	Printed Circuit Transformers (Low Boy-Low Profile)	*	LB-6230	25	I